## Network port code matching-1

If you want to add a new camera to your NVR recorder,please follow belows steps:

- 1) Move the camera closer to the NVR recorder and set up the antenna for each camera.
- 2) Power on the camera.
- 3) Connecting the NVR and camera with network cable (RJ45). The connection way of the
- NVR and camera as below picture shows.





Please scan the QR code to watch the video .

## 2 NVR Operation

Right-click to call up " Camera ".

Delete the camera that is not connected (if available) and Click on the "+" icon in the lower right corner.

	Split screen 🕨		
	Playback	<ol> <li>Camera Setup</li> </ol>	(CH1)CAM1 Recording mode Keep recording
<b>Q</b> [	Camera	Channel Recording mode Intelligent detection Alam mode (CH1) CAM1 / Recording ON	Intelligent detection Intelligent detection settings
×	System Setup	(CH2)CAM2 (CH2)	Sound alarm
11	Channel Sort	(CHO)CAMA (CHO)CAMA	Push notification Push notification BAPP EEmail Email settings
	Diagnostics	(GH)CMM7 (CHI)CMM8	Alarm period Alarm period setting
۲	Network	(CHI)CAMIO (CHII)CAMIO	Copy Camera Settings
ē	Log down 🔸		

## Network port code matching-2



Once the camera has been successfully added, click [Close].



Wait one minute, it will be finished when the screen comes out

